

CXA60 Integrated Amplifier

Jan 2015



- Audiophile grade oversize toroidal transformer and substantial extruded heat sinks delivering 2 x 60 Watts RMS into 8 Ohms
- High performance Wolfson WM8740 DAC
- RCA, S/PDIF coaxial and TOSLINK optical inputs
- Separate left and right channel heat sinks and symmetrical separated circuit paths ensure stunning stereo separation and minimal cross-channel interference
- CAP5 protection technology
- ALPs film type volume pot delivering superb low level channel balance and stereo imaging
- Support for optional BT100 Bluetooth receiver, allowing audio to be streamed from any paired aptX or A2DP Bluetooth device
- Fully switchable A and B speaker outputs
- Full metal casework with thick brushed aluminium front panel and acoustically damped metal chassis, giving enhanced resonance control
- Available in black and silver finishes

Detailed Specifications

Power output	60W RMS into 8 Ohms 90W RMS into 4 Ohms
DAC	Wolfson WM8740
Frequency Response	<5Hz – 60kHz +/-1dB
THD (unweighted)	<0.002% 1kHz at 80% of rated power <0.02% 20Hz – 20kHz at 80% of rated power
Max power consumption	600W
Standby power consumption	<0.5W
Analogue audio inputs	4 x RCA, 1 x 3.5mm MP3 input (front panel)
Digital audio inputs	1 x S/PDIF coaxial, 2 x TOSLINK optical, Bluetooth via BT100 (not supplied)
Compatibility	TOSLINK optical: 16-24 bit, 32-192kHz (using high quality TOSLINK optical cable) S/PDIF coaxial: Linear PCM 16-24 bit, 32-192kHz BT100 Bluetooth receiver: A2DP plus aptX
Outputs	Speakers A+B, 3.5mm Headphone, Preamp Output, Subwoofer Output
Dimensions (H x W x D)	115 x 430 x 341mm (4.5 x 16.9 x 13.4")
Weight	8.3kg (18.3lbs)



CXA60 Integrated Amplifier